



# ArcSight SmartConnectors

Software Version: CE 25.1

## Configuration Guide for UNIX Login and Logout SmartConnector

Document Release Date: February 2025

Software Release Date: February 2025

## Legal Notices

Open Text Corporation

275 Frank Tompa Drive, Waterloo, Ontario, Canada, N2L 0A1

## Copyright Notice

Copyright 2025 Open Text.

The only warranties for products and services of Open Text and its affiliates and licensors (“Open Text”) are as may be set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Open Text shall not be liable for technical or editorial errors or omissions contained herein. The information contained herein is subject to change without notice.

## Trademark Notices

“OpenText” and other Open Text trademarks and service marks are the property of Open Text or its affiliates. All other trademarks or service marks are the property of their respective owners.

## Documentation Updates

The title page of this document contains the following identifying information:

- Software Version number
- Document Release Date, which changes each time the document is updated
- Software Release Date, which indicates the release date of this version of the software

To check for recent updates or to verify that you are using the most recent edition of a document, go to:

<https://www.microfocus.com/support-and-services/documentation>

# Contents

Configuration Guide for UNIX Login and Logout SmartConnector ..... 4

Product Overview ..... 4

Preparing to Install the SmartConnector ..... 6

Installing and Configuring the SmartConnector ..... 7

Device Event Mapping to ArcSight Fields ..... 8

Send Documentation Feedback ..... 9

# Configuration Guide for UNIX Login and Logout SmartConnector

This guide provides information to install and configure the SmartConnector for UNIX Login and Logout and provides mappings to ArcSight ESM events. All versions of UNIX Login and Logout messages are supported.

## Intended Audience

This guide provides information for IT administrators who are responsible for managing the ArcSight software and its environment.

## Additional Documentation

The ArcSight SmartConnector documentation library includes the following resources:

- [Technical Requirements Guide for SmartConnector](#), which provides information about operating system, appliance, browser, and other support details for SmartConnector.
- [Installation and User Guide for SmartConnectors](#), which provides detailed information about installing SmartConnectors.
- [Configuration Guides for ArcSight SmartConnectors](#), which provides information about configuring SmartConnectors to collect events from different sources.
- [Configuration Guide for SmartConnector Load Balancer](#), which provides detailed information about installing Load Balancer.

For the most recent version of this guide and other ArcSight SmartConnector documentation resources, visit the [documentation site for ArcSight SmartConnectors 25.1](#).

## Contact Information

We want to hear your comments and suggestions about this book and the other documentation included with this product. You can use the comment on this topic link at the bottom of each page of the online documentation, or send an email to [MFI-Documentation-Feedback@opentext.com](mailto:MFI-Documentation-Feedback@opentext.com).

For specific product issues, [contact Open Text Support for Micro Focus products](#).

## Product Overview

This SmartConnector provides Login and Logout security. No connector-specific configuration is required.

## Preparing to Install the SmartConnector

Before you install any SmartConnectors, make sure that the OpenText ArcSight products with which the connectors will communicate have already been installed correctly (such as ArcSight ESM or ArcSight Logger).

For complete product information, refer to the *Administrator's Guide to ArcSight Platform*, available on [ArcSight Documentation](#).

If you are adding a connector to the ArcSight Management Center, see the *ArcSight Management Center Administrator's Guide* available on [ArcSight Documentation](#) for instructions.

Before installing the SmartConnector, make sure that the following are available:

- Local access to the machine where the SmartConnector is to be installed
- Administrator passwords

# Installing and Configuring the SmartConnector

1. Start the installation wizard.
2. Follow the instructions in the wizard to install the core software.
3. Specify the relevant [Global Parameters](#), when prompted.
4. From the **Type** drop-down list, select **UNIX Login/Logout** as the type of connector, then click **Next**.
5. Enter the required SmartConnector parameters to configure the SmartConnector, then click **Next**.

Parameter	Description
Custom Host Name	Enter the name of the host for which events are being collected. This host name is used to map the given value to the Device Host Name field and not for collecting logs from the specified host.

6. Select a [destination and configure parameters](#).
7. Specify a name for the connector.
8. (Conditional) If you have selected **ArcSight Manager** as the destination, the certificate import window for the ArcSight Manager is displayed. Select **Import the certificate to the connector from destination**, and then click **Next**. The certificate is imported and the **Add connector Summary** window is displayed.



**Note:** If you select Do not import the certificate to connector from destination, the connector installation will end.

9. Select whether you want to install the connector as a service or in the standalone mode.
10. Complete the installation.
11. [Run the SmartConnector](#).

For instructions about upgrading the connector or modifying parameters, see [Installation and User Guide for SmartConnector](#).

## Device Event Mapping to ArcSight Fields

The following section lists the mappings of ArcSight data fields to the device's specific event definitions. See the *ArcSight Console User's Guide* for more information about the ArcSight data fields.

ArcSight ESM Field	Device-Specific Field
Destination Host Name	Host
Destination User Name	User
Device Custom String 1	Line (Device Name)
Device Event Class ID	Action
Device Host Name	_CUSTOM_HOST_NAME
Device Product	'Unix'
Device Receipt Time	Date
Device Vendor	'Unix'
Name	Action
Source Host Name	Host



# Send Documentation Feedback

If you have comments about this document, you can [contact the documentation team](#) by email. If an email client is configured on this computer, click the link above and an email window opens with the following information in the subject line:

**Feedback on Configuration Guide for UNIX Login and Logout SmartConnector  
(SmartConnectors CE 25.1)**

Just add your feedback to the email and click send.

If no email client is available, copy the information above to a new message in a web mail client, and send your feedback to [MFI-Documentation-Feedback@opentext.com](mailto:MFI-Documentation-Feedback@opentext.com).

We appreciate your feedback!